

| Product Name | | Video Doorbell 2K (Wired) | Video Doorbell 2K (Battery-Powered) |
|-----------------------------|---|---|---|
| Product Image | |  |  |
| Video Doorbell | Max Resolution | 2K Resolution (2560x1920) | 2K Resolution (2560x1920) |
| | Adv. Image Features | HDR, Distortion Correction | WDR (hardcoded enabled) |
| | Night Vision Range | 16ft (5m) | 16ft (5m) |
| | 2-way Audio | Full Duplex | Full Duplex |
| | Power Supply | Existing Doorbell Wiring (16-24VAC, 30VA or above) or 19V-0.6A DC Power Adapter | Built-in Battery or Existing Doorbell Wiring (8-24V) |
| | Connect to Existing Doorbell Wires | Y | Y |
| | Battery Capacity | N/A | 6500mAh, nonreplacable |
| | Battery Life | N/A | 6-Month (* In the condition of 10 events per day, 20s recording length each.) |
| | Charging Time from 0% to 100% | N/A | 3 Hours on 5V 2A, 6 Hours on 5V 1A |
| | Smart Detection | Human Body and Face Detection | Human Body and Face Detection |
| | Motion Sensor (PIR Sensor) | N/A | Y |
| | Wi-Fi | Standard IEEE802.11 B/G/N | Proprietary 2.4GHz Wi-Fi |
| | Connect to Home Wi-Fi | Y | N, Only to eufy HomeBase |
| | Connect to eufy HomeBase | Developing | Y, currently HomeBase2, will support HomeBase1 soon. |
| | BLE | Y | N/A |
| | 433MHz Wireless | Y | N/A |
| | Storage on Doorbell | 4GB eMMC | N/A |
| | Video Storage Location | On Doorbell | On HomeBase |
| | Device to pair with | Indoor Chime | HomeBase |
| | Dimensions | 4.8in x 1.7in x 0.9in | 5.5in x 2.1in x 1.1in |
| Weatherproof | IP65 | IP65 | |
| Operating Temperature | -4°F - 122°F (-20°C - 50°C) | -4°F - 122°F (-20°C - 50°C) | |
| Indoor Chime | Speaker | Y | N/A |
| | Volume Adjustment | Y | N/A |
| | Number of Ringtones | 8 | N/A |
| | Wi-Fi | N/A | N/A |
| | 433MHz Wireless | Y | N/A |
| | Form Factor | Wall Plug | N/A |
| | Power Requirement | 100-240VAC | N/A |
| | Pair with | Video Doorbell 2K (Wired) | N/A |
| HomeBase | Storage | N/A | 16GB eMMC |
| | Wi-Fi | N/A | IEEE802.11 B/G/N |
| | Sub-1G (Works with eufy Sensors) | N/A | Y |
| | Power Requirement | N/A | 12V-2A Power Adapter |
| Pair with | N/A | Video Doorbell 2K (Battery-Powered) and eufyCam series | |
| Doorbell Chime Notification | Use Provided Chime | Y, up to 4 chimes | N/A |
| | Use HomeBase Speaker as Chime | N/A | Y |
| | Use Original Mechanical Chime | N | Y, with wire connection |
| | Use Original Digital Chime | N | Y, with wire connection |
| | Use Alexa Echo Series as Chime | Y, when doorbell is pressed | Y, when doorbell is pressed |
| | Use Google Home Series as Chime | N, Google doesn't open this feature yet | N, Google doesn't open this feature yet |
| Third-party Services | Compatible with Alexa (Live Stream) | Y | Y |
| | Works with Alexa (Doorbell Pressing Announcement) | Y | Y |
| | Works with GVA (Live Stream) | Y | Y |
| | Works with GVA (Doorbell Pressing Announcement) | N, Google doesn't open this feature yet | N, Google doesn't open this feature yet |
| | Works with HomeKit | N | Evaluating the possibility |
| Key Features | 3s Pre-buffer | Y | N |
| | Human Detection | Y | Y |
| | Face Detection | Y | Y |
| | Facial Recognition | N | N |
| | Notification with Face Snapshot | Y | Y |
| | Pre-recorded Quick Response | Y | Y |
| | Activity Zone | Y | Y |
| | Ignored Zone | Y | N |
| | Interact with other eufy cameras and sensors | In Software Roadmap | In Software Roadmap |
| | Security Mode (Home/Away/Schedule/Geofencing) | Y | Y |